

OV9650 Color CMOS SXGA (1.3 MegaPixel) CAMERACHIP™ with OmniPixel® Technology

General Description

The OV9650 CAMERACHIP™ is a low voltage CMOS image sensors that provides the full functionality of a single-chip SXGA (1280x1024) camera and image processor in a small footprint package. The OV9650 provides full-frame, sub-sampled or windowed 8-bit/10-bit images in a wide range of formats, controlled through the Serial Camera Control Bus (SCCB) interface.

This product has an image array capable of operating at up to 15 frames per second (fps) in SXGA resolution with complete user control over image quality, formatting and output data transfer. All required image processing functions, including exposure control, gamma, white balance, color saturation, hue control, white pixel canceling, noise canceling, and more, are also programmable through the SCCB interface. In addition, OmniVision CAMERACHIPS use proprietary sensor technology to improve image quality by reducing or eliminating common lighting/electrical sources of image contamination, such as fixed pattern noise, smearing, etc., to produce a clean, fully stable color image.

Features

- High sensitivity for low-light operation
- Low operating voltage for embedded portable applications
- Standard SCCB interface
- Supports SXGA, VGA, QVGA, QQVGA, CIF, QCIF, QQCIF, and windowed outputs with Raw RGB, RGB (GRB 4:2:2), YUV (4:2:2) and YCbCr (4:2:2) formats
- VarioPixel® method for sub-sampling formats (VGA, QVGA, QQVGA, CIF, QCIF, and QQCIF)
- Automatic image control functions including: Automatic Exposure Control (AEC), Automatic Gain Control (AGC), Automatic White Balance (AWB), and Automatic Black-Level Calibration (ABLC)
- Image quality controls including color saturation, hue, gamma, sharpness (edge enhancement), lens correction, white pixel canceling, and noise canceling

Applications

- Cellular Phones
- Picture Phones
- Toys
- PC Multimedia
- Digital Still Cameras

Key Specifications

Active Array Size		1300 x 1028
Power Supply	Core	1.8VDC \pm 10%
	Analog	2.45 to 2.8 VDC
	I/O	2.5V to (V _{DD-A} +0.3V)
Power Requirements	Active	50 mW (15 fps, no I/O power)
	Standby	30 μ W
Temperature Range	Operation	-20°C to 70°C
	Stable Image	0°C to 50°C
Output Formats (8-bit)		<ul style="list-style-type: none"> • YUV/YCbCr 4:2:2 • GRB 4:2:2 • Raw RGB Data
Lens Size		1/4"
Maximum Image Transfer Rate	SXGA	15 fps
	VGA	30 fps
	QVGA, QQVGA, CIF	60 fps
	QCIF, QQCIF	120 fps
Sensitivity		0.9 v/Lux-sec
S/N Ratio		40 dB
Dynamic Range		62 dB
Scan Mode		Progressive
Maximum Exposure Interval		1050 x t _{ROW}
Gamma Correction		Programmable
Pixel Size		3.18 μ m x 3.18 μ m
Dark Current		30 mV/s at 60°C
Well Capacity		28 K e
Fixed Pattern Noise		<0.03% of V _{PEAK-TO-PEAK}
Image Area		4.13 mm x 3.28 mm
Package Dimensions		5095 μ m x 5715 μ m

Ordering Information

Product	Package
OV09650-KL1A (Color, Lead-free)	CSP-28



OV 0 9 6 5 0 - K L 1 A

OmniVision Technologies

Resolution

- 01 = Linear sensor
- 02 = 2 MegaPixel digital sensor
- 03 = 3 MegaPixel digital sensor
- 04 = 4 MegaPixel digital sensor
- 05 = 5 MegaPixel digital sensor/
Low resolution analog sensor
- 06 = CIF digital sensor/
Low resolution analog sensor
- 07 = VGA digital sensor/
Full resolution analog sensor
- 08 = SVGA digital sensor
- 09 = SXGA 1.3 MegaPixel digital sensor
- 10 = High Dynamic Range (HDR) sensor

Type

(Analog vs. Digital, Color vs. B&W)

- 1 = B&W digital
- 4 = B&W analog
- 6 = Color digital
- 9 = Color analog

Major Iteration of Chip

Minor Iteration of Chip

- 0 = Color sensor with microlens
- 1 = B&W sensor with microlens
- 2 = Color sensor with microlens shift
- 3 = Sensor using CSP2 packaging
- 4 = Additional or custom features
- 5 = Additional or custom features
- 8 = SMIA-compliant sensor (except OV7648)

Grade

- A, B, or C
- V = Automotive grade

Package Features

- 0 = 48-pin
- 1 = 28-pin
- 2 = 24-pin
- 3 = 48-pin (large cavity CLCC)
- 4 = 16-pin
- 5 = 36-pin
- 6 = 22-pin
- 7 = 42-pin
- 8 = 40-pin

If Package Type = G or W, then:

- 0 = Chip probing
- 1 = No chip probing

Chip Features

- 0 = Digital sensor
- 1 = Analog NTSC sensor
- 2 = Analog PAL sensor
- L = Lead-free package

If Package Type = G or W, then:

- 0 = No backgrinding
- 1 = Custom
- 2 = Standard backgrinding (300 µm)

Package Type

- C = Ceramic
- P = Plastic
- K = Chip Scale Package (CSP)
- Q = Quad Flat Package (QFP)
- V = CSP2
- G = Die (for COB applications)
- W = Wafer

www.ovt.com

OmniVision reserves the right to make changes to their products or to discontinue any product or service without further notice. 'OmniVision', the OmniVision logo, 'VarioPixel', and 'OmniPixel' are registered trademarks of OmniVision Technology. All other trademarks are the property of their respective owners.

